

762



768



This highly flexible range of receivers can be used as a stand-alone unit or linked to other systems to provide radio integration.

Applications include signalling the opening or closing of doors or windows and the remotely switching of connected devices such as lights, doors and machines.

Includes two relay outputs that can be connected to many building management systems (BMS) to indicate alarm sensor activation.

At a glance...

- Internal and external aerials to increase radio range
- Allows radio contacts/PIR/shock sensors to be added without extra cabling
- Built-in LEDs and sounder
- Compatible i-on and current Menvier radio outputs

Variants

Part No	Description
762rEUR-00	Two channel radio receiver
768rEUR-50	Eight channel radio receivers, expandable to 32 channels with the 769r
769rEUR-50	Eight channel expander for use with the 768r

Compatibility

	Description
EXP-R10	10 zone radio expander
EXP-R30	30 zone radio expander
792, 794 & 797	External aerials
8600	Relay card for use with 768 and 769
All current Eaton security transmitters	

Technical specification

	762	768	769
Channels	2	8	8
Devices per channel	4	4	4
Alarm outputs	2 Relay contacts	2 Relay contacts	2 Relay contacts
LED indicators	8	16	16
Programming display	Two x seven-segment LED	Two x seven-segment LED	Two x seven-segment LED
Power consumption	55mA	55mA	55mA
Wireless frequency	868.6625 MHz	868.6625 MHz	868.6625 MHz
Internal aerial	Yes	Yes	No